






Where Data Lives: Physics, Logic, and the RAID 5 Myth

PHYSICS (HDD), LOGIC (RAID 5) breakdown of non-volatile storage.
A mechanical and mathematical breakdown of **NON-VOLATILE STORAGE (SSD)**



Registers, cache, and main memory share an embarrassing weakness: pull the power, and everything vanishes.

For photos and files to survive a decade unplugged, the system abandons electrical loops and relies on entirely different physics: manipulating **magnetism** and **trapping electrons**.



THE MECHANICAL SCALE OF MAGNETISM

THE PLATTER:

Coated in magnetic film. Divided into tiny regions where direction dictates a 0 or 1. Motor turns at 5,400 or 7,200 RPM.

THE ACTUATOR HEAD:


Reads and writes via electromagnetism. It never touches the platter.

THE SCALE METAPHOR:

The head flies 15 nanometers above the platter. At scale, this is equivalent to a commercial airliner cruising at top speed just a few millimeters above the ground without ever scraping.

GIANT MAGNETORESISTANCE

Reading data relies on materials whose electrical resistance changes in a magnetic field.




Discovered in 1988, stacking magnetic and non-magnetic films makes electrical resistance insanely sensitive spike to faint magnetic changes. This effect—Giant Magnetoresistance—allowed read heads to shrink while increasing track density.

This exact mechanism won the 2007 Nobel Prize in Physics.


THE PHYSICAL LIMIT OF THE WRITE HEAD

While Giant Magnetoresistance allowed read heads to shrink, the write head stubbornly cannot. Make it too small, and it lacks the magnetic punch to flip the platter's regions.




THE GALAXY-BRAINED HACK: SHINGLED MAGNETIC RECORDING (SMR)

Drive makers needed narrower tracks, but couldn't shrink the write head. The solution? Let the wide head simply plow through the tracks, treating data like overlapping roof shingles.



SOLID-STATE MECHANICS: TRAPPING ELECTRONS


Solid-state drives (SSDs) abandon the moving platters and actuator arms entirely. Instead of manipulating magnetism, they lock electrons up directly inside an insulator.



HDDs
MECHANICAL
MOVING PARTS
MAGNETISM
NANOMETER FLYING HEIGHTS


SSDs
SOLID STATE
ZERO MOVING PARTS
QUANTUM MECHANICS
TRAPPED PARTICLES

The Mechanics of Quantum Tunneling




The Density Ladder of NAND Flash

String these transistors into an array matching a NAND gate's wiring, and you get NAND flash—named by Toshiba's Fujio Masuoka because it was "fast as lightning."




The Logic of Survival

Physics guarantees one thing: any single disk will eventually die. To protect data from physical decay, the system must zoom out to mathematical logic.



The Array Matrix: Trading Space for Safety



RAID 0
(The Reckless One)

Chops and scatters data in parallel. Multiplied throughput. Lose any disk, lose everything.

Pure speed, zero safety.



RAID 1
(The Safe One)

Writes identical copies to every disk. Mutual backups. Tolerates failure.

Costs 50% of raw capacity.



RAID 5
(The Contested Middle)

Chops data, but computes and tucks in a parity block. Tolerates one disk failure.

Sacrifices one disk's worth of space.




RAID 6
(The Vault)

Computes a second parity group.

Survives two simultaneous failures.

The Parity Engine: XOR

RAID 5 relies on computing parity through an XOR (Exclusive OR) gate—conceptually similar to "addition without the carry."



The Horror Story




99%

"After RAID 5 loses a disk, the rebuild fails up to 99% of the time."

This is the industry nightmare that keeps IT professionals awake. It sounds mathematically inevitable. But where does this calculation actually come from, and is it true?

The Math of Catastrophe



Debunking the Myth, Part 1: Hardware Realities

The 96% failure math is too harsh because it assumes theoretical maximums represent daily reality.

Datasheet Maximum



The Maximum:

The 1 in 10^{14} datasheet URE metric is a conservative hardware maximum to protect manufacturers, not an everyday guarantee of failure.

Empirical Reality (Google)




The Reality:

In practice, UREs are not that frequent. A comprehensive Google paper tracking massive drive arrays found the highest annual drive failure rate over five years was only about 8.6%.


Debunking the Myth, Part 2: The Perspective Shift

Why should one bad data block doom the entire array?



Hardware RAID (The Problem):

The RAID card only sees raw data blocks, not files. When it hits a URE, it panics. It stops the rebuild and waits for human intervention. The array hasn't collapsed; the hardware just bailed. Most data is still there.



ZFS / RAIDZ1 (The Solution):

Smart file systems see the actual file layer. On a URE, ZFS tells you exactly which file broke, isolates it, and continues the rebuild. You make the call file by file.

Redundancy is Not Immortality

The bottom line is that RAID—whether RAID 5, RAID 6, or ZFS—never promises that “your data cannot be lost.”


Axiom 1: It only promises that you can spend a few extra physical disks to buy a logical layer of continuity during a hardware failure.

Axiom 2: Mathematical redundancy is not a substitute for a true, external, off-site backup. Physics always wins eventually.



HDD Platter

Magnetic Storage



SSD Floating-Gate Transistor



XOR Logic Gate

Mathematical Parity